

LED Wet Location Exit & Emergency

Fire retardant polycarbonate enclosure
Battery Backup & Self Diagnostic

Wet Location LED exit and emergency lights include self diagnostic tests with notification of any failures or malfunctions. Each exit sign includes an optional second face. Long lasting LED sources without maintenance for egress lighting where splashing, non-corrosive liquids and dripping may occur.

FEATURES

- 120-277VAC input
- Lumens / Wattage:
NE-970: 310lm / 2.5W per head
NX-617-LED: 2.4W
NEX-720-LED: 90lm / 0.75W per head
- 90 minutes of operation during power loss
- Battery Backup with Self Diagnostic Testing
- Brownout and Short Circuit Protection
- High temperature maintenance free NiCad battery
- Polycarbonate plastic enclosure with flame retardant
- Wet location rated
- Self Diagnostic Testing and Manual Test Switch
- Exit signs offer cold weather heating pad
- Mounting hardware included
- UL Listed and meet NFPA 70 and 101 requirements
- California Energy Commission (CEC) compliant



LED WET LOCATION EXIT & EMERGENCY

DESCRIPTION	LETTER COLOR	OPTIONAL
NEX-720-LED Exit & Emergency	/G Green Letters	-CC Cold Weather Location
NX-617-LED Exit Sign	/R Red Letters	

NE-970 Emergency Light

Ex: **NX-720-LED/G-CC** = Exit & Emergency Combo, White Housing with Green Letters for Cold Weather Location



NEX-720-LED
Exit & Emergency
Combination



NE-970
Emergency Lights



NX-617-LED
Exit Sign

